



A&F Series Transformer Type Battery Chargers FOR SLA BATTERIES



Features

- Electronically regulated** - current limited chargers for sealed lead-acid type batteries.
- Wall mount plug-in design** for 250, 300, 500, 800 series and 61000A; counter top design for 241000A, 2000, 4000 and 10A series.
- Operating temperature range:** 32°F - 104°F (0°C - 40°C).
- Input voltage:** 110/120 VAC, 60Hz. 122000A and 241000A can be switched to accept 220/230 VAC, 50Hz.
- LED's:** For 250A & 500A series: "POWER ON" and "CHARGING MODE" (ON=high-rate charging, OFF=float charging). For 300, 800, 1000, & 10A series: "FLOAT" and "FAST CHARGE" indicators. For 2000A, 241000A and 4000 series: single tri-color indicator.
- Hi-impact resistant thermo-plastic housing** for 250, 300, 500, and 800 series; metal housing for 1000, 2000, 4000, and 10A series.
- Screw-type terminals** for 250 & 500 series, I/O cord with battery connectors for 300, 800, 1000, 2000, 4000 and 10A series chargers.

Operating Characteristics

- "A" Series:** Automatic dual rate chargers sense battery requirements and automatically switch from the fast charge to float mode, or vice versa. LED's provide visual indication of the charging mode. Automatic chargers combine the advantages of float and cycle chargers; recharge time is short yet batteries are safe from being overcharged. This charger is ideal for cyclic applications where recharge time is critical and the battery may be left on charge indefinitely. As a result charging is fool-proof.
- "F" Series:** Float chargers are designed to provide optimum life for batteries used in standby applications where charging is continuous. The chargers deliver a constant voltage of 2.25 to 2.30 volts per cell which allow the battery to seek its own current level and maintain itself in a fully charged condition. This series is best suited for burglar and fire alarm equipment, emergency lighting, memory protection, or UPS systems where the battery serves as back-up power to the AC source.

Specifications

Model	Nominal Voltage	Output Voltage Float/Fast	Output Current (mA)	Type	Dimensions: in. (mm)			Weight lbs. (kg)
					Length	Width	Height	
PSC-6300A	6	6.84 / 7.35	300	Dual Rate	2.75 (69)	2.75 (70)	3.75 (95)	1.36 (0.62)
PSC-61000A	6	6.84 / 7.35	1000	Dual Rate	2.75 (70)	2.75 (70)	3.75 (95)	1.36 (0.62)
PSC-12800A	12	13.68 / 14.70	800	Dual Rate	2.75 (69)	2.75 (70)	3.75 (95)	1.36 (0.62)
PSC-122000A	12	13.50 / 14.70	2000	Dual Rate	5.55 (141)	3.60 (91)	2.89 (73)	3.80 (1.73)
PSC-124000A	12	13.50 / 14.70	4000	Dual Rate	6.65 (169)	5.30 (135)	3.40 (86)	7.40 (3.36)
PSC-124000AP	12	13.80 / NA	4000	Charger/Pwr. Supply	6.65 (169)	5.30 (135)	3.40 (86)	7.40 (3.36)

SLA Charger Selection Guide

Charger Model	Max Output (mA)	Use with Battery		U.L./CSA Listing
		Voltage	Capacity	
PSC-6300A	300	6	1 - 3 AH	CSA/NRTL*
PSC-61000A	1000	6	5 - 10 AH	CSA/NRTL*
PSC-12800A	800	12	4 - 8 AH	CSA/NRTL*
PSC-122000A**	2000	12	8 - 20 AH	CSA
PSC-124000A**	4000	12	20 - 40 AH	CSA
PSC-124000AP	3500	12	12- 40 AH	CSA

** PSC-122000A and PSC-124000A can be switched to accept 115 VAC or 230 VAC input (47-63 Hz) allowing usage both here and abroad.

Calculating Recharge Time

Recharge time depends on the depth of the preceding discharge and the output current of the charger. To determine the approximate recharge time of a fully discharged battery, divide the battery's amp. hrs. by the rated output current of the charger and multiply the resulting number of hours by a factor of 1.75 to compensate for the declining output current during the charge cycle. If the amount of amp. hrs. discharged from the battery is known, use it instead of the battery's capacity to make the calculation.

To ensure safe and efficient operation always refer to our Charger Operating Instructions, as published on our website.



Power-Sonic does not offer chargers for batteries with capacities higher than 100 AH. If you have any queries or difficulties in locating a suitable charger for batteries above 100AH, our Technical department will be happy to help.

Contact Information

www.power-sonic.com

SALES
Tel: +1-619-661-2020
Fax: +1-619-661-3650
nationalsales@power-sonic.com

CUSTOMER SERVICE
Tel: +1-619-661-2030
Fax: +1-619-661-3648
customer-service@power-sonic.com

TECHNICAL SUPPORT
Tel: +1-619-661-2020
Fax: +1-619-661-3648
technical-support@power-sonic.com

CORPORATE OFFICE • 7550 Panasonic Way • San Diego, CA 92154 • USA • Tel: +1-619-661-2020 • Fax: +1-619-661-3650

0917 1M