TRUSTED BATTERY SOLUTIONS
















PSH-1255FR 12V 6.0 AH @ 20-hr. 24 W/Cell @ 15-min.

Rechargeable Sealed Lead Acid Battery PSH - High-Rate Series

TERMINALS (mm)

F2: Quick disconnect tabs, 0.250" x 0.032" - Mate with AMP. INC FASTON "250" series



Torque - Not Applicable


FEATURES

- Absorbent Glass Mat (AGM) technology for superior performance
- Designed specifically for high-rate discharge applications
- Valve regulated, maintenance free spill proof construction
- Exceptionally high energy density
- Constant power (watts/cell)
- Rugged vibration and impact resistant ABS case and cover flame retardant to UL94-V0

APPROVALS

- Approved for transport by air. D.O.T., I.A.T.A., F.A.A. and C.A.B. certified
- U.L recognized
- ISO9001:2015 Quality management systems


DIMENSIONS inch (mm)



3.54 (90) **W**: 2.76 (70) H: 3.98 (101) **HT**: 4.21 (107)

Tolerances are +/- 0.04 in. (+/- 1mm) and +/- 0.08 in. (+/- 2mm) for height dimensions. All data subject to change without notice





CORPORATE HEADQUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA)

Power-Sonic Corporation

7550 Panasonic Way, San Diego, California 92154

T: +1 (619) 661 2020 F: +1 (619) 661 3650

E: customer-service@power-sonic.com

POWER-SONIC EUROPE LIMITED

(EMEA - EUROPE, MIDDLE EAST AND AFRICA)

3 Buckingham Square, Hurricane Way, Wickford, Essex SS11 8YQ

T: +44 (0)1268 560686 F: +44 (0)1268 560902

E: salesEMEA@power-sonic.com

	PERFORMANCE SPECIFICATIONS					
	Nominal Voltage	12 volts (6 cells)				
	Nominal Power (15 min.)	41 W/Cell				
	Rated Capacity 20-hr. (525mA to 10.50 volts) 10-hr. (1.00A to 10.50 volts) 5-hr. (1.87A to 10.20 volts) 1-hr. (6.82A to 9.00 volts) 15-min. (17.2A to 9.00 volts)	10.50 AH 10.00 AH 9.35 AH 6.82 AH 4.30 AH				
	Approximate Weight	7.00 lbs. (3.18 kg)				
	Internal Resistance (approx.)	17.0 milliohms				
	Max Discharge Current (5 Sec.)	31.5 amperes				
	Max Short-Duration Discharge Current (10 Sec.)	105.0 amperes				
	Shelf Life (% of nominal capacity at 68°F (20°C) 1 Month 3 Month 6 Month	97% 91% 83%				
	Operating Temperature Range Charge Discharge	5°F (-15°C) to 122°F (50°C) -4°F (-20°C) to 140°F (60°C)				
	Case and Cover	Flame Retardant ABS Plastic UL94:V-0				
	Power Sonic Chargers	PSC-122000A-C PSC-122000-PC				




PSH-1255FR 12V 6.0 AH @ 20-hr. 24 W/Cell @ 15-min.

Rechargeable Sealed Lead Acid Battery
PSH - High-Rate Series

CONSTANT POWER DISCHARGE (WATTS/CELL) AT 25°C (77°F) Model Final Voltage Watts per Cell @ 25°C (68°F) 5min 10min 15min 20min 30min 45min 60°C


Model	Finai	Watts per ben @ 25 0 (00 1)						
	Voltage -	5min	10min	15min	20min	30min	45min	60min
	1.75	38	27	22	17	12	9.5	6.4
PSH-1255FR	1.70	39	28	23	17.5	12.5	9.6	6.5
	1.67	40	29	24	18	13	9.8	6.7

DISCHARGE CHARACTERISTICS



Discharge Time

SHELF LIFE & STORAGE



CORPORATE HEADQUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA)

Power-Sonic Corporation

7550 Panasonic Way, San Diego, California 92154

T: +1 (619) 661 2020 F: +1 (619) 661 3650

E: customer-service@power-sonic.com

POWER-SONIC EUROPE LIMITED

(EMEA – EUROPE, MIDDLE EAST AND AFRICA)

3 Buckingham Square, Hurricane Way, Wickford, Essex SS11 8YQ

T: +44 (0)1268 560686 F: +44 (0)1268 560902

E: salesEMEA@power-sonic.com

CHARGING

Cycle Applications: Apply constant voltage charge at 2.35v/c - 2.45v/c (14.1 - 14.7v for 12v Monobloc) at 20°C. Initial charging current should be set at less than 0.25C Amps. Switch to float charge to avoid overcharging.

"Float" or "Stand-By" Service: Apply constant voltage charge of 2.25v/c – 2.30v/c (13.5 to 13.8 volts for 12v Monobloc at 20°C. When held at this voltage, the battery will seek its own current level and maintain itself in a fully charged condition.

Temperature Compensation: Charging Voltage for both Cyclic and Standby applications should be regulated in relation to ambient temperature. As temperature rises charging voltage should be reduced to prevent overcharge and increased as temperature falls to avoid undercharge.

For further charging information including temperature compensation factors, see Power Sonic Technical Manual/Power Sonic Charger specifications.

APPLICATIONS

- UPS
- Telecoms
- Data Center
- Fire and Security

CHARGERS

Power Sonic offers a wide range of chargers suitable for batteries with a variety of capacities.

Please refer to our website for more information on our switch mode and transformer type chargers.

Please contact our technical department for advice if you have difficulty in locating a suitable charger.

FURTHER INFORMATION

Please refer to our website **www.power-sonic.com** for a complete range of useful downloads, such as product catalogs, material safety data sheets (MSDS), ISO certification, etc.