

TRUSTED BATTERY SOLUTIONS

















PSPL-12100 12V 111.4 AH @ 20-hr. 12V 101.0 AH @ 10-hr.

Rechargeable Pure Lead Acid Battery PSPL - Pure Lead Series

TERMINALS: mm (inch)



DIMENSIONS: mm (inch)



CORPORATE HEADQUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA)

Power-Sonic Corporation

7550 Panasonic Way, San Diego, California 92154

T: +1 (619) 661 2020

F: +1 (619) 661 3650

E: customer-service@power-sonic.com

FEATURES

- TTPL (Thin Plate Pure Lead) technology provides superior cyclic and float performance
- High stable voltage delivery
- Durable to the harshest environments
- Rapid charging acceptance
- Shelf life more than double that of conventional lead acid batteries
- Wide operating temperature
- Front terminal design suited for 19" & 21" cabinets
- Flame Retardant ABS Plastic UL94:V-0

APPROVALS

- Approved for transport by air. D.O.T., I.A.T.A., F.A.A. and C.A.B. certified
- U.L. recognized
- ISO9001:2015 Quality management systems

PERFORMANCE SPECIFICATIONS

Nominal Voltage		12 volts (6 cells)
Rated Capacity		
20-hr.	(5.57A to 10.80 volts)	111.4 AH
10-hr.	(10.1A to 10.80 volts)	101.0 AH
5-hr.	(17.9A to 10.50 volts)	89.5 AH
1-hr.	(69.8A to 10.02 volts)	69.8 AH
Approximate Weight		69.0 lbs. (31.20 kg)
Internal Resistance (approx.)		5.47 milliohms
Shelf Life (% of nominal capacity at 68°F (20°C) 1 Month 3 Month 6 Month		98.5% 97% 91%
0 WORLD 91/6		
Operating Temperature Range Charge Discharge		5°F (-15°C) to 122°F (50°C) -4°F (-20°C) to 140°F (60°C)
Case		Flame Retardant ABS Plastic UL94:V-0

change without notice.

3 Buckingham Square,

Essex SS11 8YQ

Hurricane Way, Wickford,

T: +44 (0)1268 560686

F: +44 (0)1268 560902

POWER-SONIC EUROPE LIMITED

(EMEA - EUROPE, MIDDLE EAST AND AFRICA)


E: salesEMEA@power-sonic.com



PSPL-12100 12V 111.4 AH @ 20-hr. 12V 101.0 AH @ 10-hr.

Rechargeable Pure Lead Acid Battery
PSPL – Pure Lead Series

TERMINAL VOLTAGE (V) VS. DISCHARGE TIME (25°C, 77°F)



CHARGING

Cycle Applications: Apply constant voltage charge at 2.35v/c - 2.45v/c (14.1 - 14.7v for 12v Monobloc) at 20°C. Initial charging current should be set at less than 0.25C Amps. Switch to float charge to avoid overcharging.

"Float" or "Stand-By" Service: Apply constant voltage charge of 2.25v/c – 2.30v/c (13.5 to 13.8 volts for 12v Monobloc at 20°C. When held at this voltage, the battery will seek its own current level and maintain itself in a fully charged condition.

Temperature Compensation: Charging Voltage for both Cyclic and Standby applications should be regulated in relation to ambient temperature. As temperature rises charging voltage should be reduced to prevent overcharge and increased as temperature falls to avoid undercharge.

For further charging information including temperature compensation factors, see Power Sonic Technical Manual/Power Sonic Charger specifications.

APPLICATIONS

- UPS
- Data Centre
- Telecommunications
- · Emergency Lighting
- Utility

CORPORATE HEADQUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA) (EMEA – EURO)

Power-Sonic Corporation

7550 Panasonic Way, San Diego, California 92154

- T: +1 (619) 661 2020
- F: +1 (619) 661 3650
- E: customer-service@power-sonic.com


POWER-SONIC EUROPE LIMITED

(EMEA - EUROPE, MIDDLE EAST AND AFRICA)

3 Buckingham Square, Hurricane Way, Wickford, Essex SS11 8YQ

- T: +44 (0)1268 560686
- F: +44 (0)1268 560902
- E: salesEMEA@power-sonic.com

CAPACITY RETENTION CHARACTERISTIC



CHARGERS

Power Sonic offers a wide range of chargers suitable for batteries with a variety of capacities.

Please refer to our website for more information on our switch mode and transformer type chargers.

Please contact our technical department for advice if you have difficulty in locating a suitable charger.

FURTHER INFORMATION

Please refer to our website **www.power-sonic.com** for a complete range of useful downloads, such as product catalogs, material safety data sheets (MSDS), ISO certification, etc.

