



| Invested Battery Solutions                             | HUBBER<br>DATA<br>DATA<br>DATA<br>DATA<br>DATA<br>DATA<br>DATA<br>DAT  |  |
|--|--|--|
| Super Sport Series   | CONVENTIONAL BATTERY   |  |
| TERMINALS: (mm)  | FEATURES   |  |
|  | High performance conventional lead acid battery  |  |
|  | <ul> <li>Engineered to protect against corrosion and withstand<br/>vibration</li> </ul>  |  |
|  | Dry pre-charged battery construction   |  |
|  | Delivers high cranking power   |  |
|  | <ul> <li>Acid pack and vent tube included for initial filling</li> </ul>   |  |
| Front View Side View Top View  | Long shelf life, with no need to recharge before initial filling   |  |
|  | Suitable for all weather conditions  |  |
|  | Requires ongoing maintenance   |  |
| DIMENSIONS: inch (mm)  | PERFORMANCE SPECIFICATIONS   |  |
| L: 5.28 (134)<br>W: 3.19 (81)<br>H: 6.30 (160)<br>Tolerances are +/- 0.04 in. (+/- 1mm)<br>and +/- 0.08 in. (+/- 2mm) for height<br>dimensions. All data subject to<br>change without notice.      | Nominal Voltage  | 12 volts   |
|  | Rated Capacity           10-hr.         (1.20A)           5-hr.         (1.97A)           2-hr.         (4.20A)           1-hr.         (7.20A)           0.5-hr.         (12.96A) | 12.00 AH<br>9.84 AH<br>8.40 AH<br>7.20 AH<br>6.48 AH |
|  | Cold Cranking Amps (CCA)   | 165  |
|  | Cranking Amps (CA)   | 195  |
|  | Approximate Battery Weight (with acid)<br>Approximate Electrolyte Weight   | 8.95 lbs. (4.06 kg)<br>1.98 lbs. (0.90kg)            |
|  | Self Discharge (77°F (25°C)  | Approximately 3% per month                           |
|  | The Effect of Temperature on Capacity<br>104 °F (40°C)<br>77 °F (25°C)<br>32 °F (0°C)<br>5 °F (-15°C)  | 106%<br>100%<br>86%<br>65%                           |
| GLOBAL HEADQUARTERS<br>(USA AND INTERNATIONAL EXCLUDING EMEA)       POWER-SONIC EMEA<br>(EMEA - EUROPE, MIDDLE EAST AND AFRICA)         Power-Sonic Corporation       Smitspol 4, 3861 RS Nijkerk, | Case   | ABS Plastic  |
|  | Recommended Charger  | Please contact Power Sonic                           |
| 365 Cabela Dr Suite 300,         The Netherlands           Reno, Nevada 89523         T NL: + 31 33 7410 700   |  |  |
| USA         T UK: + 44 1268 560 686           T: +1 619 661 2020         T FR: + 33 344 32 18 17           E: customer-service@power-sonic.com         E: salesEMEA@power-sonic.com                |  |  |

0

Ð

- UPPER LEVEL -

E

To ensure safe and efficient operation always refer to the latest edition of our Technical Manual, as published on our website. © 2020. Power-Sonic Corporation. All rights reserved. All trademarks are the property of their respective owners. All data subject to change without notice. E&O.E






# **CB12A-A** 165 CCA 12V 12Ah @ 10-hr.

Conventional Lead Acid Powersport Battery Super Sport Series

#### **DISCHARGE CHARACTERISTICS**



For further charging information including temperature compensation factors, see Power Sonic Technical Manual/Power Sonic Charger specifications.

## **CHARGERS**

Power Sonic offers a wide range of chargers suitable for batteries with a variety of capacities.

Please refer to our website for more information on our switch mode and transformer type chargers.

Please contact our technical department for advice if you have difficulty in locating a suitable charger.

### **FURTHER INFORMATION**

Please refer to our website **www.power-sonic.com** for a complete range of useful downloads, such as product catalogs, material safety data sheets (MSDS), ISO certification, etc.





## **CHARGING**

**Constant Voltage Charge:** Apply constant voltage charge at 14.4 V - 15.0 V at  $77^{\circ}\text{F}$  ( $25^{\circ}\text{C}$ ). Initial charging current should be set at less than 3.6 Amps. Charging time 16 - 24 hours.

**Constant Current Charge:** Charging current 0.1C=1.2 Amps, when charging voltage up to 15.6 V, continue to charge 2 hours.

**"Float" or "Stand-By" Charge:** Apply constant voltage charge of 13.5 V - 13.8 V at 77°F (25°C). When held at this voltage, the battery will seek its own current level and maintain itself in a fully charged condition.

**Temperature Compensation:** Charging voltage should be regulated in relation to ambient temperature. As temperature rises charging voltage should be reduced to prevent overcharge and increased as temperature falls to avoid undercharge.

## **APPLICATIONS**

- Motorcycle
- Watersport
- Scooter
- ATV
- UTVSnowmobile
- GLOBAL HEADOUARTERS

(USA AND INTERNATIONAL EXCLUDING EMEA) Power-Sonic Corporation 365 Cabela Dr Suite 300, Reno, Nevada 89523 USA T: +1 619 661 2020

E: customer-service@power-sonic.com

POWER-SONIC EMEA (EMEA – EUROPE, MIDDLE EAST AND AFRICA) Smitspol 4, 3861 RS Nijkerk, The Medical and

 Lawn & Garden

The Netherlands T NL: + 31 33 7410 700 T UK: + 44 1268 560 686 T FR: + 33 344 32 18 17 E: salesEMEA@power-sonic.com

To ensure safe and efficient operation always refer to the latest edition of our Technical Manual, as published on our website. © 2020. Power-Sonic Corporation. All rights reserved. All trademarks are the property of their respective owners. All data subject to change without notice. E&0.E